

## Product

<b>Code</b>		
P935070 00002	IGEA BT	Operatore irreversibile elettromeccanico 24 V per cancelli battenti fino a 250 kg di peso e 2.5 m di lunghezza.



## THALIA

### Control panel for one or two 24V operators for swing gates



#### THALIA D113745 00002

Application: control panel for one or two 24V operators for swing gates

Board power supply: 230V single-phase

Operators power supply: 24Vdc 180W max each operator

Main features: removable terminal blocks with new standard colour-coding, simplified scenario-based programming with display and incorporated dual channel receiver, D-Track anti-crushing system, slowdown during opening and closing and electronic self-learning

Main functions: automatic re-closing, fast closing, partial opening, deadman feature

Compatibility: LIBRA C MA, LIBRA, LIBRA R, LIBRA MA R

## Technical features


	IGEA BT
Control unit	THALIA
Operator weight	16 kg
Operator type	electromechanical swing operators with articulated arm
Power supply	24 V
Power input	40 W
Maximum angle	125 °
Cycle time	15 sec
Type of limit switch	electromechanical
Slowdown	yes
Impact reaction	d-track
Locking	mechanical
Release	knob operated with personal key
Frequency of use	intensive
Environmental conditions	from -15 °C to 60 °C

## ACCESSORIES



#### THALIA P - D113747 00002

Control panel for one or two 24V operators for swing gates



#### BIR C - N190104

Rubber safety edge (H 30 mm), price per m



#### LRV - P135005

Bras court pour IGEA, IGEA BT - LRV



#### BOX - N574039

Wall-mounted safe for steel cable release and electric control




#### RADIUS B LTA 24 R1 - D113748 00003

Flashing beacon with built-in antenna for 24V motors Flashing light without incorporated antenna for motors with power supply 24 V.



#### RADIUS B LTA 24 R2 - D113749 00003

Flashing beacon without built-in antenna for 24V motors Flashing light without incorporated antenna for motors with power supply 24 V.



#### B 00 R02 - P123025

Wall mounting for B LTA series flashing beacons



#### Mitto B Rcb02 R1 - D111904

Transmitter with channels. Range . Power supply with 1 battery type 23 A

## ACCESSORIES



**Q.BO TOUCH - P121024**  
Wireless digital touch button panel  
433Mhz rolling code.



**Q.BO KEY WM - P121022**  
Key selector for outdoor use with double contact.



**DESME A15 - P111526**  
Pair of self-aligning photocells. Range 30 m. Power supply 24 V ac/dc. Pair of self-aligning photocells. Range 30 m. Power supply 24 V ac/dc.



**PHP - P903018**



**BBT BAT - P125020**  
Set of backup batteries for THALIA and THALIA P